

## SC-41-0200-0001-99 SmartCell Dual Input/Output Device for Fire Zones

### Overview

---

The SmartCell Input / Output Device is quick and easy to install and offers individual addressing at the SmartCell Control Panel.

Features include two resistor monitored inputs, two voltage free outputs and bidirectional 868 MHz communication.

This device is third party certified and compatible with the full SmartCell product range.



### Details

---

- Full wireless communication with panel
- Quick and easy to install
- Two resistor monitored inputs
- Two voltage free outputs
- For connection to remote fire devices

# SC-41-0200-0001-99

## SmartCell Dual Input/Output Device for Fire Zones

### Technical specifications

---

#### Input

Input quantity	2
Input type and rating	Resistor monitored inputs

#### Output

Output quantity	2
Output type and rating	Voltage free outputs, rated 1 A at 30 VDC

#### General

Wireless frequency	868 MHz
--------------------	---------

#### Physical

Physical dimensions	150 x 200 x 55 mm (W x H x D)
Net weight	0.45 kg
Mounting type	Wall mount
Batteries	3 x ER14505M 3.6 V lithium thionyl chloride batteries (Fanso or HCB)

#### Environmental

Operating temperature	-10 to +55°C
Storage temperature	-10 to +30°C (with batteries) -10 to +55°C (without batteries)
Relative humidity	95% noncondensing max.
Environment	Indoor

#### Standards & regulation

Compliance	CE
Certification	CPR
Standards	EN54-13 EN54-18 EN54-25

# **ASTECC**<sub>B.V.</sub>

Kerkweg 70  
6155 KN Puth (NL)  
Tel.: +31 (0)46 443 55 77  
Fax: +31 (0)46 443 04 82  
E-mail: [info@astec.nl](mailto:info@astec.nl)  
Internet: [www.astec.nl](http://www.astec.nl)